

BCD Adder



❑ So before heading towards the new approach, let's again discuss the HIGHEST possible number in addition of two 4-bit BCD

HIGHEST NUMBER USING 4-BIT BCD- 9

HIGHEST NUMBER USING 4-BIT BCD- 9

DON'T FORGET TO INCLUDE THE CARRY OF PREVIOUS STAGE- 1

19

Bcd adder (sum up to 9)



Number	C	S3	S2	S1	S0
0	0	0	0	0	0
1	0	0	0	0	1
2	0	0	0	1	0
3	0	0	0	1	1
4	0	0	1	0	0
5	0	0	1	0	1
6	0	0	1	1	0
7	0	0	1	1	1
8	0	1	0	0	0
9	0	1	0	0	1



Bcd adder (sum is 10 to 19)

Number	C	S3	S2	S1	S0
10	1	0	0	0	0
11	1	0	0	0	1
12	1	0	0	1	0
13	1	0	0	1	1
14	1	0	1	0	0
15	1	0	1	0	1
16	1	0	1	1	0
17	1	0	1	1	1
18	1	1	0	0	0
19	1	1	0	0	1

Bcd adder (sum is 10 to 19)



BCD adder sum

Number	C	S3	S2	S1	S0
10	1	0	0	0	0
11	1	0	0	0	1
12	1	0	0	1	0
13	1	0	0	1	1
14	1	0	1	0	0
15	1	0	1	0	1
16	1	0	1	1	0
17	1	0	1	1	1
18	1	1	0	0	0
19	1	1	0	0	1

Binary sum

K	s3	s2	s1	s0
0	1	0	1	0
0	1	0	1	1
0	1	1	0	0
0	1	1	0	1
0	1	1	1	0
0	1	1	1	1
1	0	0	0	0
1	0	0	0	1
1	0	0	1	0
1	0	0	1	1



When is the result > 9

Binary sum

Number	K	S3	S2	S1	S0
10	0	1	0	1	0
11	0	1	0	1	1
12	0	1	1	0	0
13	0	1	1	0	1
14	0	1	1	1	0
15	0	1	1	1	1
16	1	0	0	0	0
17	1	0	0	0	1
18	1	0	0	1	0
19	1	0	0	1	1

C = K +



When is the result > 9

Binary sum

Number	K	S3	S2	S1	S0
10	0	1	0	1	0
11	0	1	0	1	1
12	0	1	1	0	0
13	0	1	1	0	1
14	0	1	1	1	0
15	0	1	1	1	1
16	1	0	0	0	0
17	1	0	0	0	1
18	1	0	0	1	0
19	1	0	0	1	1

$$C = K + S3 * S2 +$$



When is the result > 9

Binary sum

Number	K	S3	S2	S1	S0
10	0	1	0	1	0
11	0	1	0	1	1
12	0	1	1	0	0
13	0	1	1	0	1
14	0	1	1	1	0
15	0	1	1	1	1
16	1	0	0	0	0
17	1	0	0	0	1
18	1	0	0	1	0
19	1	0	0	1	1

$$C = K + S3*S2 + S3*S1$$

Inputs: [A]=0101, [B]= 0011, C₀=0

